

形式表記例：3極、50A フレーム、7.5kA、15A の場合 BW50SAT-3P015 の様に下記表の形式の後に続けて極数（2P または 3P）と電流値（3桁表記）で示す。

| | 7.5 | 10 | 15 | 20 | 30 | 50 | 75 | 100 | 150 | 200 |
|---------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------|
| | 9.841 | 13.122 | 19.682 | 26.243 | 39.365 | 65.608 | 98.412 | 131.216 | 216.506 | 288.675 |
| | 231.268 | 308.358 | 462.536 | 616.715 | 708.566 | 1180.944 | 1771.416 | 2361.887 | 3897.114 | 5196.152 |
| BW50SAT-3P015 | BW32SAT-3P020 | BW32SAT-3P030 | BW50SAT-3P040 | BW100EAT-3P060 | BW100EAT-3P090 | BW250EAT-3P125 | BW250EAT-3P150 | BW250EAT-3P225 | BW400EAT-3P350 | |
| BW50SAT-3P015 | BW32SAT-3P020 | BW32SAT-3P030 | BW50SAT-3P040 | BW100EAT-3P060 | BW100EAT-3P090 | BW250EAT-3P125 | BW250EAT-3P150 | BW250EAT-3P225 | BW400EAT-3P350 | |
| BW50SAT-3P015 | BW32SAT-3P020 | BW32SAT-3P030 | BW50SAT-3P040 | BW100EAT-3P060 | BW100EAT-3P090 | BW250EAT-3P125 | BW250EAT-3P150 | BW250EAT-3P225 | BW400EAT-3P350 | |
| BW50RAG-3P020 | BW50RAG-3P040 | BW50RAG-3P050 | BW100EAG-3P060 | BW100EAT-3P060 | BW100EAT-3P090 | BW250EAT-3P125 | BW250EAT-3P150 | BW250EAT-3P225 | BW400EAT-3P350 | |
| | BW125JAG-3P015 | BW125JAG-3P060 | | BW125JAT-3P060 | BW125JAT-3P090 | BW250EAT-3P125 | BW250EAT-3P150 | BW250EAT-3P225 | BW400EAT-3P350 | |
| | BW125JAG-3P015 | BW125JAG-3P060 | | BW125JAT-3P060 | BW125JAT-3P090 | BW250RAT-3P125 | BW250RAT-3P150 | BW250RAT-3P225 | BW400EAT-3P350 | |
| | BW125RAG-3P015 | BW125RAG-3P060 | | BW125RAG-3P100 | BW250RAT-3P125 | BW250RAT-3P125 | BW250RAT-3P150 | BW250RAT-3P225 | BW400RAT-3P350 | |
| | BW125RAG-3P015 | BW125RAG-3P060 | | BW125RAG-3P100 | BW250RAT-3P125 | BW250RAT-3P125 | BW250RAT-3P150 | BW250RAT-3P225 | BW400RAT-3P350 | |
| | BW50HAG-3P015 | BW125HAG-3P060 | | BW125HAG-3P100 | BW250HAG-3P150 | BW250HAG-3P225 | BW400HAG-3P300 | BW630HAG-3P500 | | - |

| | 7.5 | 10 | 15 | 20 | 30 | 50 | 75 | 100 | 150 | 200 |
|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------|----------|----------|
| | 19.682 | 26.243 | 39.365 | 52.486 | 78.730 | 131.216 | 196.824 | 262.432 | 393.648 | 524.864 |
| | 462.536 | 616.715 | 925.073 | 1233.430 | 1417.132 | 2361.887 | 3542.831 | 4723.775 | 7085.662 | 9447.550 |
| BW32SAT-3P030 | BW50SAT-3P040 | BW50SAT-3P050 | BW100EAT-3P075 | BW100EAT-3P100 | BW250EAT-3P150 | BW400EAT-3P250 | BW400EAT-3P300 | | - | - |
| BW32SAT-3P030 | BW32SAT-3P040 | BW50SAT-3P050 | BW100EAT-3P075 | BW100EAT-3P100 | BW250EAT-3P150 | BW400EAT-3P250 | BW400EAT-3P300 | | - | - |
| BW50SAT-3P030 | BW50SAT-3P040 | BW50SAT-3P050 | BW100EAT-3P075 | BW100EAT-3P100 | BW250EAT-3P150 | BW400EAT-3P250 | BW400EAT-3P300 | | - | - |
| BW50RAG-3P050 | BW100EAG-3P060 | BW100EAT-3P060 | BW100EAT-3P075 | BW100EAT-3P100 | BW250EAT-3P150 | BW400EAT-3P250 | BW400EAT-3P300 | | - | - |
| BW125JAG-3P060 | | BW125JAT-3P060 | BW125JAT-3P075 | BW125JAT-3P090 | BW250EAT-3P150 | BW400EAT-3P250 | BW400EAT-3P300 | | - | - |
| BW125JAG-3P060 | | BW125JAT-3P060 | BW125JAT-3P075 | BW125JAT-3P090 | BW250RAT-3P150 | BW400EAT-3P250 | BW400EAT-3P300 | | - | - |
| BW125RAG-3P060 | BW125RAG-3P100 | BW250RAG-3P125 | | BW250RAT-3P125 | BW250RAT-3P150 | BW400RAT-3P250 | BW400RAT-3P300 | | - | - |
| BW125RAG-3P060 | BW125RAG-3P100 | BW250RAG-3P125 | | BW250RAT-3P125 | BW250RAT-3P150 | BW400RAT-3P250 | BW400RAT-3P300 | | - | - |
| BW125HAG-3P060 | BW125HAG-3P100 | BW250HAG-3P125 | BW250HAG-3P175 | BW400HAG-3P250 | BW400HAG-3P300 | BW630HAG-3P500 | BW630HAG-3P600 | | - | - |

| | 7.5 | 10 | 15 | 20 | 30 | 50 | 75 | 100 |
|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|
| | 17.045 | 22.727 | 34.091 | 45.455 | 68.182 | 113.636 | 170.455 | 227.273 |
| | 426.136 | 568.182 | 852.273 | 1136.364 | 1704.545 | 2840.909 | 4261.364 | 5681.818 |
| | | BW32SAT-2P030 | BW50SAT-2P045 | BW125JAT-2P060 | BW125JAT-2P090 | BW250EAT-2P175 | BW400EAT-2P300 | BW400EAT-2P400 |
| | | BW32SAT-2P030 | BW50SAT-2P045 | BW125JAT-2P060 | BW125JAT-2P090 | BW250EAT-2P175 | BW400EAT-2P300 | BW400EAT-2P400 |
| | | BW50SAT-2P030 | BW50SAT-2P045 | BW125JAT-2P060 | BW125JAT-2P090 | BW250EAT-2P175 | BW400EAT-2P300 | BW400EAT-2P400 |
| BW50RAG-2P040 | BW63RAG-2P060 | | BW125JAT-2P060 | BW125JAT-2P090 | BW250EAT-2P175 | BW400EAT-2P300 | BW400EAT-2P400 | |
| BW125JAG-2P060 | | | BW125JAT-2P060 | BW125JAT-2P090 | BW250EAT-2P175 | BW400EAT-2P300 | BW400EAT-2P400 | |
| BW125JAG-2P060 | | | BW125JAT-2P060 | BW125JAT-2P090 | BW250RAT-2P175 | BW400EAT-2P300 | BW400EAT-2P400 | |
| BW125RAG-2P060 | BW125RAG-2P075 | BW125RAG-2P125 | | BW125RAT-2P090 | BW250RAT-2P175 | BW400RAT-2P300 | BW400RAT-2P400 | |
| BW125RAG-2P060 | BW125RAG-2P075 | BW125RAG-2P125 | | BW125RAT-2P090 | BW250RAT-2P175 | BW400RAT-2P300 | BW400RAT-2P400 | |
| BW125HAG-3P060 | BW125HAG-2P075 | BW125HAG-2P125 | BW250HAG-2P150 | BW400HAG-2P250 | BW400HAG-2P400 | | | - |

| | 7.5 | 10 | 15 | 20 | 30 | 50 | 75 | 100 |
|----------------|----------------|----------------|----------------|----------------|----------------|----------------|--------|---------|
| | 34.1 | 45.5 | 68.2 | 90.9 | 136.4 | 227.3 | 340.9 | 454.5 |
| | 852.3 | 1136.4 | 1704.5 | 2272.7 | 3409.1 | 5681.8 | 8522.7 | 11363.6 |
| BW50EAT-2P045 | BW100EAT-2P075 | BW125JAT-2P100 | BW250EAT-2P150 | BW250EAT-2P200 | BW400EAT-2P400 | BW630RAT-3P600 | | - |
| BW50EAT-2P045 | BW100EAT-2P075 | BW125JAT-2P100 | BW250EAT-2P150 | BW250EAT-2P200 | BW400EAT-2P400 | BW630RAT-3P600 | | - |
| BW50SAT-2P045 | BW100EAT-2P075 | BW125JAT-2P100 | BW250EAT-2P150 | BW250EAT-2P200 | BW400EAT-2P400 | BW630RAT-3P600 | | - |
| BW100EAG-2P100 | BW100EAT-2P075 | BW125JAT-2P100 | BW250EAT-2P150 | BW250EAT-2P200 | BW400EAT-2P400 | BW630RAT-3P600 | | - |
| BW125JAT-2P060 | BW125JAT-2P075 | BW125JAT-2P100 | BW250EAT-2P150 | BW250EAT-2P200 | BW400EAT-2P400 | BW630RAT-3P600 | | - |
| BW125JAT-2P060 | BW125JAT-2P075 | BW125JAT-2P100 | BW250RAT-2P150 | BW250RAT-2P200 | BW400EAT-2P400 | BW630RAT-3P600 | | - |
| BW125RAG-2P125 | BW250RAG-2P150 | BW250RAG-2P225 | BW250RAT-2P150 | BW250RAT-2P200 | BW400RAT-2P400 | BW630RAT-3P600 | | - |
| BW125RAG-2P125 | BW250RAG-2P150 | BW250RAG-2P225 | BW250RAT-2P150 | BW250RAT-2P200 | BW400RAT-2P400 | BW630RAT-3P600 | | - |
| BW125HAG-2P125 | BW250HAG-2P150 | BW250HAG-2P225 | BW400HAG-2P300 | BW630HAG-3P500 | | | | - |