



(b) 400 ~ 440V

電磁接触器形式	サーマルリレー形式	電動機定格		遮断器定格電流 (A)	短絡容量 (kA)			
		出力 (kW)	電流 (A)		1.5	2.5	7.5	10
SC-03	TR-0N	0.2	0.65	3/5	BW32AAG-3P003 EW32EAG-3P005	<input type="checkbox"/> W32SAG-3P003	<input type="checkbox"/> W50SAG-3P005	
		0.4	1.15					
		0.75	1.8	5		<input type="checkbox"/> W32SAG-3P005		
		1.5	3.1					
		2.2	4.6					
		10	<input type="checkbox"/> W32AAG-3P010	<input type="checkbox"/> W32SAG-3P010	<input type="checkbox"/> W50SAG-3P010	<input type="checkbox"/> W50RAG-3P010		
SC-0、05	TR-0N	3.7	7.5	15	<input type="checkbox"/> W32AAG-3P015	<input type="checkbox"/> W32SAG-3P015	<input type="checkbox"/> W50SAG-3P015	<input type="checkbox"/> W50RAG-3P015
SC-4-0	TR-5-1N	5.5	11.5	15/20	<input type="checkbox"/> W32AAG-3P020	<input type="checkbox"/> W32SAG-3P020	<input type="checkbox"/> W50SAG-3P020	<input type="checkbox"/> W50RAG-3P020
SC-4-1、5-1	TR-5-1N	7.5	14.5	20/30	<input type="checkbox"/> W32AAG-3P030	<input type="checkbox"/> W32SAG-3P030	<input type="checkbox"/> W50SAG-3P030	<input type="checkbox"/> W50RAG-3P030
SC-N1	TR-N2	11	21	30/40	<input type="checkbox"/> W50AAG-3P040	<input type="checkbox"/> W50EAG-3P040	<input type="checkbox"/> W50SAG-3P040	<input type="checkbox"/> W50RAG-3P040
SC-N2	TR-N2	15	27.5	40/50	<input type="checkbox"/> W50AAG-3P050	<input type="checkbox"/> W50EAG-3P050	<input type="checkbox"/> W50SAG-3P050	<input type="checkbox"/> W50RAG-3P050
SC-N2S	TR-N3	18.5	34	50/60				
SC-N2S	TR-N3	22	39	60/75	<input type="checkbox"/> W63EAG-3P060		<input type="checkbox"/> W63SAG-3P060	<input type="checkbox"/> W63RAG-3P060
SC-N3	TR-N3	30	54	100	<input type="checkbox"/> W100EAG-3P100			
SC-N4	TR-N5	37	65	100/125				
SC-N5A	TR-N5	45	78	150	<input type="checkbox"/> W250EAG-3P150			
SC-N6	TR-N6	55	95	200	<input type="checkbox"/> W250EAG-3P200			
SC-N7	TR-N7	75	130	250	<input type="checkbox"/> W250EAG-3P250			
SC-N8	TR-N8	90	155	300	<input type="checkbox"/> W400EAG-3P300			
SC-N10	TR-N10	110	188	350	<input type="checkbox"/> W400EAG-3P350			
SC-N11	TR-N12	132	224	400	<input type="checkbox"/> W400EAG-3P400			

電磁接触器形式	サーマルリレー形式	電動機定格		遮断器定格電流 (A)	短絡容量 (kA)				
		出力 (kW)	電流 (A)		18	30	36	50	65
SC-03	TR-0N	0.2	0.65	3/5					
		0.4	1.15						
		0.75	1.8	5					
		1.5	3.1						
		2.2	4.6						
		10							
SC-0、05	TR-0N	3.7	7.5	15	<input type="checkbox"/> W125JAG-3P015	<input type="checkbox"/> W125RAG-3P015	<input type="checkbox"/> W50HAG-3P015		
SC-4-0	TR-5-1N	5.5	11.5	15/20					
SC-4-1、5-1	TR-5-1N	7.5	14.5	20/30	<input type="checkbox"/> W125JAG-3P020	<input type="checkbox"/> W125RAG-3P020	<input type="checkbox"/> W50HAG-3P020		
SC-N1	TR-N2	11	21	30/40	<input type="checkbox"/> W125JAG-3P030	<input type="checkbox"/> W125RAG-3P030	<input type="checkbox"/> W50HAG-3P030		
SC-N2	TR-N2	15	27.5	40/50	<input type="checkbox"/> W125JAG-3P040	<input type="checkbox"/> W125RAG-3P040	<input type="checkbox"/> W50HAG-3P040		
SC-N2S	TR-N3	18.5	34	50/60	<input type="checkbox"/> W125JAG-3P060	<input type="checkbox"/> W125RAG-3P060	<input type="checkbox"/> W125HAG-3P060		
SC-N2S	TR-N3	22	39	60/75	<input type="checkbox"/> W125JAG-3P075	<input type="checkbox"/> W125RAG-3P075	<input type="checkbox"/> W125HAG-3P075		
SC-N3	TR-N3	30	54	100	<input type="checkbox"/> W125JAG-3P100	<input type="checkbox"/> W125RAG-3P100	<input type="checkbox"/> W125HAG-3P100		
SC-N4	TR-N5	37	65	100/125	<input type="checkbox"/> W125JAG-3P125	<input type="checkbox"/> W125RAG-3P125	<input type="checkbox"/> W125HAG-3P125		
SC-N5A	TR-N5	45	78	150	<input type="checkbox"/> W250EAG-3P150	<input type="checkbox"/> W250JAG-3P150	<input type="checkbox"/> W250RAG-3P150	<input type="checkbox"/> W250HAG-3P150	
SC-N6	TR-N6	55	95	200	<input type="checkbox"/> W250EAG-3P200	<input type="checkbox"/> W250JAG-3P200	<input type="checkbox"/> W250RAG-3P200	<input type="checkbox"/> W250HAG-3P200	
SC-N7	TR-N7	75	130	250	<input type="checkbox"/> W250EAG-3P250	<input type="checkbox"/> W250JAG-3P250	<input type="checkbox"/> W250RAG-3P250	<input type="checkbox"/> W250HAG-3P250	
SC-N8	TR-N8	90	155	300	<input type="checkbox"/> W400EAG-3P300	<input type="checkbox"/> W400SAG-3P300	<input type="checkbox"/> W400RAG-3P300	<input type="checkbox"/> W400HAG-3P300	
SC-N10	TR-N10	110	188	350	<input type="checkbox"/> W400EAG-3P350	<input type="checkbox"/> W400SAG-3P350	<input type="checkbox"/> W400RAG-3P350	<input type="checkbox"/> W400HAG-3P350	
SC-N11	TR-N12	132	224	400	<input type="checkbox"/> W400EAG-3P400	<input type="checkbox"/> W400SAG-3P400	<input type="checkbox"/> W400RAG-3P400	<input type="checkbox"/> W400HAG-3P400	